

2 Humbucker + 4 Pole 5 Way Switch + Volume + Tone : Rev D

Switch : Oak Grigsby 4 Pole 5 Way

1 Volume

1 Tone

1: Neck*

2: Neck* + .033mF Cap //

Bridge* : HOOP

3: Neck* // Bridge*

4: Neck IC + Bridge IC

5: Bridge*

Color Codes : Lollar

Left to Right Switch Numbering

rev : D

date : 2013-01-04

Key :

OF Outer Finish

OS Outer Start

IF Inner Finish

IS Inner Start

* Pickup internally in Series

~ Pickup internally in Parallel

+ two components in Series


// two components in Parallel

IC Inner Coil

OC Outer Coil

OOP Out Of Phase

HOOP Half Out Of Phase



*Note 1: Neck pickup **rotated 180°** to achieve inner Screw coil South polarity

*Note 2: This circuit is designed for two low to medium output PAF type pickups with non-identical coils - one screw, one slug
If used with two pickups with matching coils, ie, Dual Screw or Dual Blade pickups, P4 may sound very similar to P3

4WINDS
LUTHERIE

© 2013 Four Winds Lutherie | fourwindslutherie.com
licensed under CC BY-NC-SA 4.0.
To view a copy of this license, visit
<https://creativecommons.org/licenses/by-nc-sa/4.0>